

If you look at the contents of `_cm_output_multi()` you will see a switch statement like the following:

```
$outarray = array();

switch ($name) {
  case 'multi1':
    // return a non-empty array to print an empty line
    $outarray[] = array('dummy' => "");
    break;

  case 'multi2':
    // return a non-empty array to print an empty line
    $outarray[] = array('dummy' => "");
    break;

  case 'multi3':
    // return a non-empty array to print an empty line
    $outarray[] = array('dummy' => "");
    break;

  case 'multi4':
    // return a non-empty array to print an empty line
    $outarray[] = array('dummy' => "");
    break;

  ....

  default:
    // return a non-empty array to print an empty line
    $outarray[] = array('dummy' => "");
    break;
} // switch

return $outarray;
```

Each time this method is called it has a different 'multiN' value in `$name`, so within the relevant 'case' statement you require code to construct `$outarray` before it is returned. You are currently outputting both a label and a text field for each line, so in the situation where the text field is empty and you do not want the line printed at all then do nothing as `$outarray` is already empty. If you put ANYTHING at all in `$outarray` then the line WILL be printed even if there are no values to print.
